

## USER'S MANUAL

### LED Zoom Par 18x18W RGBWA UV lighting



#### **1-Maintenance**

- 1.Please keep the light in dryness and avoiding use in wet place.**
- 2.Using intermittently can be extended the life.**
- 3.Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.**
- 4.Please do not wipe the crust using organic menstruum for avoid to damaged the product.**

#### **2-Statement**

**The product has well capability and intact packing when leave factory,All of the user should comply with above warning item and manual ,any misuse cause of the damages are not included in our guarantee,and also can't be responsible for any malfunction & problem owing to ignore the manual. Please forgive that we will not be notice for technical change**

#### **3-Attention Item**

- 1.For guarantee the life of product,please do not put it on the wet place and not use it the place over 40 degree.**
- 2.Please don't lay the product on the un-fixable or shakable place.**
- 3.Ask for the professional to maintain the product in order to avoid the danger of get an electric shock.**
- 4.Power supply should not be changed over +&-10% while the light is using,it will be decreased the**

life of lamp if the power is too high, but it will be influenced the luminosity if the power is too low.

5. After power off, if it is need used again, please cool down over 20 minuter.

6. Please look round the manual for ensure the product can be used normally.

#### **4-Product Introduction**

- \* **Power Supply:AC90--275V,50--60HZ**
- \* **Power consumption:324W**
- \* **Fixing lamp:LED 18×18W RGBWA UV**
- \* **DMX-Control-channels:12 DMX Channels**
- \* **Shuttle:Flash rate:0--10HZ**
- \* **Dimmer:0-100% mechanic dimmer**
- \* **Long Lifespan LEDs(more than 60,000 hours)**

<b>Display Control Instruction</b>		
<b>Display</b>	<b>Translate</b>	<b>Function</b>
<b><i>A001-A512</i></b>	<b>DMX Address</b>	<b>Channel address code, (001--512)</b>
<b><i>AUD1-5002</i></b>	<b>Function</b>	<b>Auto 10mode ;Sound contro 2 mode</b>
<b><i>St00-St16</i></b>	<b>Strobe</b>	<b>Strobe Speed</b>
<b><i>SP01-SP16</i></b>	<b>Speed</b>	<b>Function speed</b>
<b><i>r000-r255</i></b>	<b>Red</b>	<b>Red dimming</b>
<b><i>G000-G255</i></b>	<b>Green</b>	<b>Green dimming</b>
<b><i>b000-b255</i></b>	<b>Blue</b>	<b>Blue dimming</b>
<b><i>U000-U255</i></b>	<b>White</b>	<b>White dimming</b>
<b><i>A000-A255</i></b>	<b>Amber</b>	<b>Amber dimming</b>
<b><i>P000-P255</i></b>	<b>Violet</b>	<b>Violet dimming</b>
<b><i>E000-E255</i></b>	<b>Focusing</b>	<b>Focusing adjust</b>

<b>Channel</b>	<b>Value</b>	<b>Features</b>
<b>CH1</b>	<b>0-255</b>	<b>Total light adjustment</b>
<b>CH2</b>	<b>0-255</b>	<b>Red Dimmer</b>
<b>CH3</b>	<b>0-255</b>	<b>Green Dimmer</b>
<b>CH4</b>	<b>0-255</b>	<b>Blue Dimmer</b>
<b>CH5</b>	<b>0-255</b>	<b>White Dimmer</b>
<b>CH6</b>	<b>0-255</b>	<b>Amber Dimmer</b>
<b>CH7</b>	<b>0-255</b>	<b>Violet Dimmer</b>
<b>CH8</b>	<b>0-255</b>	<b>Strobe</b>
<b>CH9</b>	<b>0-255</b>	<b>Focusing</b>
<b>CH10</b>	<b>0-255</b>	<b>Focusing Stop</b>
<b>CH11</b>	<b>0-239</b>	<b>Function</b>
	<b>240-255</b>	<b>Sound control</b>
<b>CH12</b>	<b>0-255</b>	<b>Program speed adjustment</b>