

USER'S MANUAL

LED Beam 12x12W RGBW Moving Head Lighting



Maintenance

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

Statement

The product has well capability and intact packing when leave factory, All of the user should comply with above warning item and manual, any misuse cause of the damages are not included in our guarantee, and also can't be responsible for any malfunction & problem owing to ignore the manual. Please forgive that we will not be notice for technical change

Attention Item

1. For guarantee the life of product, please do not put it on the wet place and not use it the place over 40 degree.
2. Please don't lay the product on the un-fixable or shakable place.
3. Ask for the professional to maintain the product in order to avoid the danger of get an electric shock.

4. Power supply should not be changed over $\pm 10\%$ while the light is using, it will be decreased the life of lamp if the power is too high, but it will be influenced the luminosity if the power is too low.
5. After power off, if it is need used again, please cool down over 20 minutes.
6. Please look round the manual for ensure the product can be used normally.

DMX Channel Summary-9 Channels Mode

Channel	Value	Function
CH1	0-255	X axis rotation
CH2	0-255	Y axis rotation
CH3	0-255	Total light adjustment
CH4	0-255	Red Dimmer
CH5	0-255	Green Dimmer
CH6	0-255	Blue Dimmer
CH7	0-255	White Dimmer
CH8	0-255	Strobe
CH9	0-255	XY axis rotation speed adjustment

DMX Channel Summary-16 Channels Mode

Channel	Value	Function
CH1	0-255	X axis rotation
CH2	0-255	Y axis rotation
CH3	0-255	Total light adjustment
CH4	0-255	Red Dimmer
CH5	0-255	Green Dimmer
CH6	0-255	Blue Dimmer
CH7	0-255	White Dimmer
CH8	0-255	Strobe
CH9	0-255	XY speed adjustment
CH10	8-230 231-255	color combination change Color jump Auto run mode Color gradient Auto run mode 1 Color gradient Auto run mode 2
CH11	0-255	Color Auto run mode speed adjustment
CH12	0-255	Default mode 1
CH13	150-200	Default mode speed adjustment
CH14	0-255	X-axis fine-tuning

CH15	0-255	Y-axis fine-tuning
CH16	150-200	Reset

Display Control Instruction

DMX SET	001-512	512 ADDRESS SETTINGS
Channel Set	9	9 channel control
	16	16 channel control
Show Mode	Dmx Mode	Console mode
	Fast Mode	Fast run mode
	Slow Mode	Slow run mode
	Sound Mode	Sound run mode
Sound Sense	0-99	Sound Sensitivity regulatory
Pan Inverse	OFF	X motor Positive direction
	ON	X motor Positive direction
Tite Inverse	OFF	Y motor Positive direction
	ON	Y motor Positive direction
While balance	R 0-255	Red adjustment
	G 0-255	green adjustment
	B 0-255	blue adjustment
	W 0-255	White adjustment
Default confirm	Yes	Initialization factory
Fixture REST	YES	System Reset

Display Control Instruction

Welcome to use our light. The light uses energy-saving LED, long Product life, shockproof, dustproof, DMX receiver and self-running feature, which can produce a variety of vivid lighting effects, easy to operate, suitable for all types of entertainment decoration, architectural lighting industry.


A:Function

B:Up

C:Down

D:Enter

E:LED Display



A

B

C

D

Instructions: Press the function key A cycled out the eight different function effects, digital tube first two digits on behalf of which the current function (see menu). The last two digits represent the functions in which the address code or speed parameters. Press the B or C key to modify the parameter values. Press the D key to confirm.

Product Introduction

- * Power Supply: AC90--240V, 50--60HZ
- * Power consumption: 144W
- * Fixing lamp: LED 12×12W
- * DMX-Control-channels: 9/16 DMX Channels
- * Flash rate: 0--10HZ
- * Dimmer: 0-100% mechanic dimmer
- * Long Lifespan LEDs (more than 60,000 hours)
- * Product Size: 25*15*31 cm
- * Product weight: 4.6 kg
- * Package Size: 31*20*36 cm
- * Package weight: 5.05 kg