

## **Weather Stations**

### WIFI Weather Station

Model: 0310-025T



#### **Features**

Model 0310-025T				
Temperature (indoor +outdoor)	•	Rainfall data	•	Snooze
Humidity (indoor +outdoor)	•	UV index	•	Backlight
Dew point (indoor +outdoor)	•	Light meter	•	Beeper on/off ●
PM2.5 PM1.0 (indoor)	Χ	Solar radiation	•	Max./Min value
Carbon Dioxide CO2 (indoor)	Χ	Time and calendar	•	Low power indication
Wind chill	•	USB connection	Χ	Alarm
Wind speed	•	WIFI connection	•	Wall hanging
Wind gust	•	LORA connection	Χ	Soar powered •
Wind average	•	With data storage	Χ	Calibratable
Wind direction	•	View data on APP	•	°C and °F
Add additional 8	Χ	Support Weathercloud and	•	m/s, km/h, mph, knots,
hygro-thermometer sensors	Λ	Wunderground		ft/s or bft
Barometric (REL and ABS) pressure	•	Weather forecast (24H-48H)	•	mmhg, inHg, hPa
Moon phase	•	View data on a software	Χ	W/m², fc or lux. ●



# **Weather Stations**

### **Specifications**

Measurement	Range	Accuracy	Resolution		
Indoor Temperature	0 to 60 °C	± 1 °C	0.1 °C		
Outdoor Temperature	-40 to 60 °C	± 1 °C	0.1 °C		
Indoor Humidity	10 to 99 %	± 5% (20% - 90%)	1 %		
Outdoor Humidity	10 to 99%	± 5% (20% - 90%)	1 %		
UV Index	1 to 15+	± 1	± 1		
Light meter	0 to 200k lux	± 15%	± 15%		
Rainfall	0 to 9999mm	<15mm: ±1 mm, 15mm to 9999mm: ±7%	<1000mm (0.3mm) >1000mm (1mm)		
Wind Direction	0 - 360 °	± 10° (16 points compass)	± 1º (16 points compass)		
Wind Speed	0 to 50 m/s	2m/s~10m/s: ±3m/s 10m/s~50m/s: ±10%	0.1 m/s		
Barometric Pressure	300 -1100 hpa	± 3 hpa	0.1 hpa		
Transmission interval	16s				
Transmission distance	100m in open area				
Transmission frequency	433MHz				
Max. transmission power	0.5mW				
WIFI	802.11 b/g/n, 2.4GHz				
WIFI transmission distance	20m				

### **General Information**

Model	0310-025T		
Power supply	Receiver: 3 x AAA batteries		
	Transmitter: 3 x AA batteries		
	Power adaptor: 5V/1A or 5.9V/0.5A		
Product size	Receiver:215x22x158mm		
	Transmitter:330x150x280mm		
Product weight	Receiver:250g		
	Transmitter: 1000g		
Standard accessories	Receiver x 1 / Transmitterx1/ metal gasket x 4 / U-bolt nuts x4/ U-bolt(M5) x2 / stainless steel base x		
	1/ wrench (M5) x1 / screwdriver (M3) x 1 / Rubber plug x 2 / manual x 1/ power adaptor x1		